



Service Bulletin

Trouble Shooting Procedures for Power Boards and Control Panels

Purpose

Use this bulletin to diagnose Norcold refrigerator control panels and power boards. Most problems can be linked to components controlled by the power board or voltage input to the power board. Sometimes the power board or control board will need to be replaced. Use this bulletin to determine the correct action.

Background

The electronic control system controls the refrigerator's power board and control panel. Use the electronic control system diagnostic mode to identify problems with the power board and control panel.

The electronic controls work on 10.5 to 15.4 volts DC. The AC power cord that is attached to the power board conducts 120 volts AC power from the RV receptacle to the power board. It does not provide power to the electronic controls.

Applicability

Before trying to fix or replace the control panel and power board, make sure these areas, which can be affected by the electronic controls, are working properly:

- Proper refrigerator installation
- Adequate ventilation
- Leveled operation
- AC heater(s)
- DC heater
- Burner and orifice assembly
- Fan(s)
- Heat deflector cap (flue cap)
- Flue baffle

IMPORTANT!

The power board and the control panel do not control the fans, ice maker, or the ice maker water valve.

List of Procedures

Procedure A: Checking Power Board 628661 Diagnostics Inputs and Outputs on N41X/N41X.3/N51X/N51X.3/N62X/N82X Models.

Procedure B: Checking Power Board 628661 Diagnostics Inputs and Outputs on N64X/N64X.3/N84X/N84X.3/12XX Models.

Procedure C: Checking Power Board 621267/621268 Diagnostics Inputs and Outputs on N41X/N41X.3/N51X/N51X.3/N62X/N82X Models.

Procedure D: Checking Power Board 621269/621270/621271/621272 Diagnostics Inputs and Outputs on N64X/N64X.3/N84X/N84X.3/12XX Models.

Procedure E: Checking DC Power Input to the Power Board and Power Board DC power output to the Control Panel.

Procedure F: Checking DC Power Input at the Control Panel (applies to Power Boards 621267/621268/621269/621270/621271/621272/621991).

Procedure G: Checking DC Power Input at the Control Panel (applies to Power Board 628661).

Procedure H: Checking Electronic Controls AUTO Operation (Except N61X/N8X Refrigerators).

Procedure I: Checking Electronic Controls Operation N61X/N8X Refrigerators.

Procedure A: Checking Power Board 628661 Diagnostics Inputs and Outputs – N41X / N41X.3 / N51X / N51X.3 / N62X / N82X Refrigerators

Turn ON Refrigerator and select the highest temperature setting.

Accessing Diagnostics
 1. At the same time, press and hold the TEMP SET and MODE switch buttons.
 2. Release both buttons when **1** shows on the screen.

Screen [1] Action
 The **1** turns off. If no LEDs show on the screen after the **1** turns off, replace the control panel.

Screen [2] Action
 The **2** turns off. The On LED remains lit. If any LED segments show on this screen after the screen number turns off, replace the control panel.

Screen [2] Action
 The **2** turns off. The On LED remains lit. If any LED segments show on this screen after the screen number turns off, replace the control panel.

Screen [3] Action
 The **3** turns off. After a short pause the screen displays in temperature.

Screen [3] Action
 The **3** turns off. After a short pause the screen displays in temperature.

Screen [4] Action
 Screen **4** displays the fault history stored in non-volatile memory. After the screen number turns off, the fault history LEDs display. The position of the LEDs identify recent fault items.

Screen [5] Action
 Screen **5** displays the fault history stored in non-volatile memory. After the screen number turns off, the fault history LEDs display. The position of the LEDs identify recent fault items.

Screen [4] Action
 The **4** turns off. If no LEDs show on the screen after the **4** turns off, replace the control panel.

Screen [6] Action
 Screen **6** is used to clear stored fault history. After the screen number turns off, the letters [E] and [r] show on the screen.

Screen [5] Action
 The **5** turns off. If no LEDs show on the screen after the **5** turns off, replace the control panel.

Screen [7] Action
 Screen **7** shows active inputs to the power board. After the screen number turns off, the power board input LEDs display. The position of the LEDs indicate active inputs to the power board.

Screen [6] Action
 Screen **6** shows active power board outputs. After the screen number turns off, the power board output LEDs display. The position of the LEDs indicate active outputs to the power board.

Screen [8] Action
 Screen **8** shows active power board outputs. After the screen number turns off, the power board output LEDs display. The position of the LEDs indicate active outputs to the power board.

Screen [7] Action
 Screen **7** shows active inputs to the power board. After the screen number turns off, the power board input LEDs display. The position of the LEDs indicate active inputs to the power board.

Screen [9] Action
 Screen **9** shows DC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the DC voltage input to the power board.

Screen [8] Action
 Screen **8** shows active power board outputs. After the screen number turns off, the power board output LEDs display. The position of the LEDs indicate active outputs to the power board.

Screen [10] Action
 Screen **10** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [9] Action
 Screen **9** shows DC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the DC voltage input to the power board.

Screen [10] Action
 Screen **10** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [11] Action
 Screen **11** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [12] Action
 Screen **12** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [13] Action
 Screen **13** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.


Screen [14] Action
 Screen **14** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [15] Action
 Screen **15** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.


Screen [16] Action
 Screen **16** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.

Screen [17] Action
 Screen **17** shows AC voltage input to the power board. After the screen number turns off, the LED segment that displays identifies the AC voltage input to the power board.


Procedure B: Checking Power Board 628661 Diagnostics Inputs and Outputs N64X /N64X.3 /N84X / N84X.3 /N109X / 12XX Refrigerators




Procedure C: Checking Power Board 621267 / 621268 Diagnostics Inputs and Outputs – N41X / N41X.3 / N51X / N51X.3 / N62X / N82X Refrigerators




Procedure D: Checking Power Board 621269 / 621270 / 621271 / 621272 Diagnostics Inputs and Outputs N64X / N64X.3 / N84X / N84X.3 / N109X / 12XX Refrigerators




Procedure E: Checking DC Power Input to the Power Board and Power Board DC Power Output to the Control Panel




Procedure F: Checking DC Power Input to the Control Panel




Procedure G: Power Board 628661 – Checking DC Power Input at the Control Panel



Procedure H: Checking Electronic Controls AUTO Operation (Except N61X and N81X Refrigerators)



Procedure I: Checking Electronic Controls AUTO Operation N61X and N81X Refrigerators



Perform the following checks in the order listed below with AC power available in the RV.

- Check incoming AC power at the RV outlet.
 - Voltage 108 to 132 volts AC; go to Step 2.
 - No voltage; check RV AC power distribution to the refrigerator circuit.
- Check for 108 to 132 volts AC presence at AC power cord power board plug.
 - Voltage 108 to 132 volts AC; go to Step 3.
 - No voltage; replace AC power cord.
- Check the condition of the F2 fuse (F3 in previous power boards).
 - Fuse good; go to Step 4.
 - Fuse open; check for a grounded AC heater.
- Check the condition of the F2 fuse terminal clips.
 - Clips tight and in good condition; go to Step 5.
 - Fuse clips loose; adjust clips as required.
- Connect AC power cord to the power board, then measure voltage across fuse terminals.
 - Fault corrected; voltage present and the controls select AUTO AC operation.
 - Fault NOT corrected; voltage present and the controls select AUTO LP operation.
 - Replace power board.

To correct a no flame fault:

- Make sure LP gas is available to the refrigerator.
- Make sure the refrigerator "Manual shut off" valve is open.
- Check the condition of the orifice and burner. These components should be cleaned yearly.
- Make sure the electrode air gap is 1/8 to 3/16 in.
- Check the electrode spark sense wire assembly for continuity.
- Make sure the power board is properly grounded to the refrigerator back plate.
- Check the power board T1 coil for damage. A loose coil or connector will require power board replacement.

Fault Codes displayed by N61X and N81X Control Panel LEDs

Green "ON" light flashes 1 time every 3 seconds. Thermistor or its circuit is open or shorted. The controls are in Backup Operating Mode.
 (1) Check thermistor connections.
 (2) Measure thermistor resistance. Do not replace the power board or the control panel.

Green "ON" light flashes 2 times every 3 seconds. Mode switch in control panel faulty.
 Replace the control panel.

Green "ON" light flashes 3 times every 3 seconds. AC heater or its circuit is open. Check AC heater connections and continuity.
 Do not replace the power board or the control panel.

Green "ON" light flashes 4 times every 3 seconds. The Yellow light (LP operation) is off. Flame sensing circuit fault.
 Replace the power board.

Green "ON" light flashes 5 times every 3 seconds. The Yellow light (LP operation) is off. The controls have detected a No cooling condition.
 (1) First occurrence - reset and then turn the refrigerator Off and back On.
 (2) Second occurrence - the Power Board has to be hardware reset. Do not replace the power board or the control panel.

Green "ON" light flashes 6 times every 3 seconds. The Yellow light (LP operation) is off. Probable causes:

- The open limit switch in the cooling unit canister has tripped. It may be due to poor ventilation, exceeding off-level operation limits, or a dirty burner.
- The switch connections or jumper wire is disconnected (units without the high temperature limit switch). Do not replace the power board or the control panel.